

CV TITLE	PROTOTYPES AND POSSIBLE SUBSTITUTES	Gov. SPEC.	DESCRIPTION	CV TITLE	PROTOTYPES AND POSSIBLE SUBSTITUTES	Gov. SPEC.	DESCRIPTION
CV1351 CV1352 CV1353 CV1354 CV1355	TB4/1250; TY4-500; 5868; EM80; 6BR5; OA81; OA85; ESU300; CV2947; 4049C; Replace with CV5.	COM COM COM COM MOA	Power Triode Tuning Indicator Semiconductor Diode Semiconductor Diode Rectifier	CV1396 CV1397 CV1398 CV1399 CV1400	CV279; CV1591 to CV1594; CV2137; (CV1399); (CV1398); C1C;	MOA MOA MOA MOA AD	CRT CRT CRT CRT Barretter
CV1356 CV1357 CV1358 CV1359 CV1360	U22; CV3750; CV1031; Replace with CV981. ME41; CV3565;	MOA MOA MOA MOA	Rectifier Tuning Indicator Tuning Indicator Triode	CV1401 CV1402 CV1403 CV1404 CV1405	CL33; 332 PEN CY31; OM1; DD41; CV1056; E1199;	COM COM COM COM	Pentode Rectifier Double Diode Diode
CV1361 CV1362 CV1363 CV1364 CV1365	MZ05-20; CV1025; DET16; B150; 807. See CV124. 4282BZ;	MOA MOA MOA MOA	Triode Triode Tetrode Tetrode	CV1406 CV1407 CV1408 CV1409 CV1410	CV24; PEN 45; P41; SP2 selected. See CV1320. TH2;	COM COM AD AD	Pentode Triode Pentode (Triode) Hexode
CV1366 CV1367 CV1368 CV1369 CV1370	V248A; V245; V226; 4061A; PV1/35; SW35PEN;	MOA MOA MOA MOA MOA	Pentode Pentode Pentode Pentode Pentode	CV1411 CV1412 CV1413 CV1414 CV1415	TH41; TV4; UU6; CV21; 4011A;	COM COM COM COM	(Triode) Heptode Tuning Indicator Rectifier Triode
CV1371 CV1372 CV1373 CV1374 CV1375	SW75 PEN; PZ1-75; CV1221; 4069A; 803; CV623; PY3-600; 807. See CV124. EF85; 6BY7;	MOA MOA MOA MOA COM	Pentode Pentode Pentode Tetrode Pentode	CV1416 CV1417 CV1418 CV1419	See CV1648. See CV25. See CV1300. 11D3; HAD; TDD13C; HLDD 1320; 13DHA;	COM	(Double Diode) Triode
CV1376 CV1377 CV1378 CV1379 CV1380	EF80; 6BX6; GZ34; 5AR4; 20K; CV1380; CV954; CV959; 20K; CV1379; CV954; CV959;	COM MOA AD MOA MOA	Pentode Rectifier CRT CRT	CV1420 CV1421 CV1422 CV1423 CV1424 CV1425	4078A; 869B; 2V/531E; See CV176. 3D/100A; See CV1106. 20A1. See CV1194. 7D5;	COM COM COM COM	Rectifier Triode (Triode) Hexode Pentode
CV1381 CV1382	CV1383; CV1112; CV279; CV1588; CV964; 23D; 4101;	MOA MOA	CRT CRT	CV1426 CV1427 CV1428 CV1429	EK2; EF9; CV1714; EBC3; CV1715; EL2;	COM COM COM COM	Octode Pentode (Double Diode) Triode Pentode
CV1383 CV1384 CV1385	CV1381; CV1112; 41DS; CV1131; CV960; E4504/B/16;	MOA MOA MOA	CRT CRT CRT	CV1430 CV1431 CV1432 CV1433 CV1434 CV1435	ACSP3 (RH); ACT16; CMG8; GS26; EC31; EM4; GU20; GU21; CV5; AH221;	COM AD COM COM COM	Pentode Triode Photo-cell Triode Tuning Indicator Rectifier
CV1386 CV1387 CV1388 CV1389 CV1390	ACR3; ACR4; ACR5; ACR6; CV1587;	COM COM COM COM MOA	CRT CRT CRT CRT CRT	CV1436 CV1437 CV1438 CV1439 CV1440	See CV1050. See CV1577. KT61; EL33; CV2938; 6AG6G; MT9F; MT9L;	COM COM COM COM	Tetrode Triode Triode
CV1391 CV1392 CV1393 CV1394 CV1395	CV1587; E4504/E/16; CV279; ACR17; ACR18; CV1087;	MOA MOA MOA MOA MOA	CRT CRT CRT CRT CRT				

CV1351-CV1440